

■ INCLUDED ITEMS

• BA300S JP version • USB Cable • Adhesive sheet • 4.4mm to 4.4mm balanced standard Cable

■ PARTS AND CONTROLS

Front Side



Rear Side



① 4.4mm balanced IN jack
④ Power charge indicator

② Power switch
⑤ Power charge port

③ 4.4mm balanced headphone jack

■ CHARGING THE UNIT

- ① Turn off the unit.
(The battery charges while the unit is on.)
- ② Connect the 5v 500mA~ AC adapter or PC.
Charge indicator lights up in red.
Charging is completed in about 3 hours (The time is up to the AC adapter). The indicator turns off when the battery is completely charged.

■ CONNECT THE AUDIO DEVICE

Connect the unit to the device by the 4.4mm balanced IN jack on the front panel.
(The 4.4mm to 4.4mm balanced standard cable is in the box.)

■ LISTENING TO MUSIC WITH THE HEADPHONES

- ① Turn on the unit.
- ② Connect the headphone to the unit by the 4.4mm balanced standard headphone jack on the front panel.

■ CAUTION !!!

We strongly suggest you to follow the steps above while using the unit for protecting your headphones and your ears. We will not take the responsibility if you take the wrong way in using this unit.

■ SPECIFICATIONS

Supported impedance: 8~300Ω
S/N ratio: -111dB
Maximum output: 350mW+350mW (32Ω)
THD+N: <0.02%
Battery: built-in lithium polymer rechargeable battery, approx 7hr battery life
Charging time: approx 3 hours
Size and weight: W57 x H16.5 x D120mm, 165g

Oriolus Japan

www.en.oriolus.jp

Cyras Co., Ltd.

Zipcode: 110-0016

Address: 5F, Nichiei-intec Okachimachi No.2 BLDG,
3-42-5, Taito, Taito-District, Tokyo, Japan

Tel: +81-(0)3-6869-9631